



IV、Protection


Overload short-circuit and Input reverse polarity Protection

When one of these defaults occurs and output current rises to about 1.1mA, the unit should fall in constant current mode. In case arcing, the psu will be tripped for short time and restart again

V、Dimensions

The power supply is 229mm long x 141mm wide x 35mm high.

VI、Instruction for use



1、 The modes select of hv demand by LK1

Inside---- 1、 4

Outside---- 2、 3

2、 The modes select of current demand by LK2



波尔高压电源（宿迁）有限公司
英国真维特 (GENVOLT) 高压设备公司

追求完美的高压电源制造专家

Inside---- 1、4

Outside---- 2、3

3、HV ON

Low Effective,users can connect the pin 13with pin 15.

4、HV feedback and current feedback

Users can monitor HV output by the voltage of pin 1
and also can monitor current by the voltage of pin 7

VII、Considerations

The product can generate high voltage,affecting safety of persons,so
non-professional prohibit maintenance。

波尔高压电源（宿迁）有限公司
生产基地：江苏省宿迁市宿豫经济开发区庐山路 60 号
电话：0527-88068878 传真：0527-88068028
网址：www.boherhv.com 邮箱：sales@boherhv.com
技术服务：北京市海淀区花园路 1 3 号网商世纪商务楼
B 座 1 2 0 号
电话：010-62383945 传真：010-62358289

英国真维特 (Genvolt) 高压设备有限公司
总部地址： **New Road, Highley, Bridgnorth,**
(研发中心) **Shropshire, United Kingdom WV166NN**
电话：+441746862555 传真：+441746862666
网址：www.genvolt.co.uk 邮箱：sales@genvolt.co.uk